

砂塵試驗機 Sand and Dust Tester



產品說明：

耐塵試驗機乃針對各種汽車零件做防塵耐塵試驗，其主要測試含浮塵、流塵、其測試零件包含有車燈、儀表、安全帶、座椅調整器、電器防塵套、轉向系統排檔桿軸、門鎖等，以測試其耐塵作動安全性。

Application:

Sand and dust tester is used for dust test, including floating dust and cyclone dust: for all kinds of automobile parts, such as, automobile lamps, meter, safe belt, seat regulator, dirt-proof boot of electrical appliance, lockers, etc.

特點：

- 採用強力噴塵裝置，使用者可於儀錶面板上獨立操控浮塵1、浮塵2、浮塵3之條件。
- 採用振動裝置可使每次噴塵濃度相同。
- 精密的粉塵濃度收集器，可減少因操作不當而錯估濃度。
- 可滿足DIN, IEC, GB, ISO, JIS多種測試規範要求。
- 自主研發控制系統，電腦連接監控。
- 便捷的除塵設計，操作人員不必進入箱內。
- 同步諧振功能，保證灰塵濃度一致性。

Features:

- Adopt strong spray dust device, the user can operate independently for No.1 floating dust, No.2 floating dust, No.3 floating dust on the gauge panel.
- Adopt vibration device; spray dust's density can be the same every time.
- Precision collection for dust concentration, Can reduce the misestimate concentration because of improper operation
- Meet DIN, IEC, GB, ISO, JIS standard
- Control system: be connected with and monitored by computer
- Convenient design for dust cleaning.
- Synchronous resonance function to ensure of the uniformity of dust concentration

參數規格 Technical Parameters:

| 型號 Model | DT-F1 | DT-F2 | DT-F3 | DT-C1 | DT-C2 | | |
|--|--|---------------|--------------|----------------------------|--------------------|--|--|
| 備註 Remark | F代表浮塵 / F for floating dust | | | C代表流塵 / C for cyclone dust | | | |
| 砂塵濃度 Concentration of Sand and Dust | F1: 6000mg/m³ | F2: 3000mg/m³ | F3: 100mg/m³ | C1:5000mg/m³, 5m/s | C2:100mg/m³, 10m/s | | |
| 內箱尺寸 WxHxD (mm) Internal Dimension WxHxD (mm) | 1000x1000x1000 | | | 1000x1000x1000 | | | |
| 外箱尺寸 (mm) External Dimension WxHxD (mm) | 1600x1800x1300 | | | 1650x1850x1450 | | | |
| 溫度範圍 Temperature Range | 室溫狀態 (25°C±15°C), 即試驗室溫度 RT(25°C±15°C), or lab temperature | | | | | | |
| 濕度範圍 Humidity Range | 35~90% R.H., 即試驗室濕度 35~90% R.H., or lab humidity | | | | | | |
| 滑石粉用量 Talcum Powder Dosage | 2 ~4Kg/m² | | | | | | |
| 金屬絲網標尺線徑 Metal Net Mesh Standard Diameter | 50µm | | | | | | |
| 綫間隙網間距 Diameter between Metal Wires | 75µm | | | | | | |
| 噴粉降塵形式 Powder Spray & Dust Fall Mode | 1.自由降塵式：採用離心機將砂塵吹至箱頂1/5高度，然後使其自由沉降 2.吹砂塵：底部氣壓噴塵，多階壓力可調 1. Dust fall freely: adopt centrifugal fan to blow the sand or dust to the 1/5 of roof, then fall freely. 2. Blow the sand or dust: pressure spray dust from the bottom, multi-steps pressure adjustable | | | | | | |
| 測試標準 Test Standard | 滿足JIS, ISO汽車相關測試, IEC60529, DIN40050, GB2423等相關外殼測試 Meet JIS, ISO, IEC60529, DIN40050, GB2423 test standard | | | | | | |
| 電源/ Power | AC220V ; 1φ 3線 ; 50/60HZ AC220V ; 1φ 3 Lines ; 50/60HZ | | | | | | |